

X-Band Digital Phase Shifter

P/N: JXWBYX-T-8.0-8.4-360

Item	Unit	Value
Frequency Range	GHz	8.0 – 8.4
Phase Shift Range	Deg	0 to 360
Phase Shift Resolution	Deg	11.2
Phase Accuracy	Deg	±4 max
VSWR		1.5 max
Input Level Range	dBm	-70 to -10
Control Logic		5 bits, TTL Compatible
Switching Speed	ms	1 max
Signal Gain	dB	10
Input & Output Connectors		SMA-Female
Supply Voltage	V	±5
Supply & Control Connector		15 Pin Subminiature Connector
Net Weight	Kg	0.08 Around

Outline Drawing (Size: mm)

